# **MTO106**

## **Transformer ohmmeter**



- Entry level transformer ohmmeter
- 2 channels with max 6 A current output
- ±0.25% measurement accuracy
- 48 V test voltage for fast saturation of transformers
- Multimeter type operation, intuitive and fast
- Safety through automatic, passive discharge circuitry
- True portability compact size and low weight

#### **DESCRIPTION**

The MTO106 transformer ohmmeter is an easy-to-use, line-operated instrument specifically designed for safe and accurate field measurement of winding resistance in smaller transmission and distribution transformers.

It has dual channels with a wide measurement range and can accurately provide information about the vast majority of power transformers, reactors and instrument transformers. The test current can be manually set in five different ranges to fit transformers of various sizes.

The instrument is exceedingly simple to use, which minimises the need to train service engineers. It has a single selector switch for test current and a single button to activate the test cycle. The instrument is also supplied with test leads fitted with Kelvin clamps that allow for a single, one-time connection to the unit under test. The test leads are 10 m (33 ft) in length to allow for easy testing of pole mounted transformers.

The compact and lightweight instrument is housed in a rugged plastic case for true portability. When closed, the case is rated IP67, which means your instrument will always arrive safely to the testing location even in the harshest conditions.

Users are protected by an automatic discharge function that de-energises the transformer winding at the end of every test. The discharge function is passive and thus also functions if there is an inadvertent loss of power or if the test or mains leads are accidentally pulled.

#### **APPLICATIONS**

The MTO106 is mainly intended for field measurements of smaller transmission and distribution transformers:

- To verify factory test readings.
- As part of a regular maintenance program.
- To help locate the presence of defects in transformers such as increased contact resistance in terminal connections and tap changers.

The instrument can also be used for general resistance measurements of, for instance control wiring, voltage regulators, motors, generators and all types of connections.

#### Transformer ohmmeter

# Megger.

#### **SPECIFICATIONS**

Specifications are valid at nominal input voltage. Specifications are subject to change without notice.

#### **Environment**

high-voltage substations and industrial

environments.

*Temperature* 

Operating  $-20^{\circ}\text{C}$  to  $+50^{\circ}\text{C}$  (-4°F to  $+122^{\circ}\text{F}$ ) Storage & transport  $-50^{\circ}\text{C}$  to  $+70^{\circ}\text{C}$  (-58°F to  $+158^{\circ}\text{F}$ ) Humidity (operating)  $-90^{\circ}\text{RH}$ , non-condensing

**CE-marking** 

 LVD
 2014/35/EU

 EMC
 2014/30/EU

 RoHS
 2011/65/EU

General

*Mains voltage* 100 - 240 V AC, 50/60 Hz

Input power 400 VA (max)

Case Ruggedized plastic case with removable lid

and carrying handle, IP 67 when closed

Dimensions (W x D x H) 360 x 304 x 194 mm (14.2 x12 x 7.6")

Weight 7.3 kg (16 lbs) excl. cables
Display 4-inch, backlit, monochrome

alphanumerical display

Test leads 2 x 10 m (33 ft), with banana connectors

and Kelvin clamps

Ground lead 1 x 5 m (16 ft), 2.5 mm<sup>2</sup>

#### **Measurement section**

Measurment range 10 μOhm to 30 kOhm

Resolution Up to 4 digits
Open circuit test voltage up to 48 V DC
Measurement voltage up to 20 V DC

Current	B		December 1
range	Resistance range	Inaccuracy	Resolution
6A 10.00 mΩ to 5.00		±(0.25%rdg+1digit)	4 digits
	$0.010\text{m}\Omega\text{to}9.999\text{m}\Omega$	$\pm (0.25\% \text{rdg} + 2 \text{ digits})$	0.001 mΩ
1 A	100.0 mΩ to 30.00 Ω	±(0.25%rdg+1digit)	4 digits
	$0.10\text{m}\Omega$ to $99.99\text{m}\Omega$	$\pm (0.25\% \text{rdg} + 2 \text{ digits})$	0.01 mΩ
100 mA	1.000 Ω to 300.0 Ω	±(0.25%rdg+1digit)	4 digits
	$1.0\mathrm{m}\Omega$ to $999.9\mathrm{m}\Omega$	$\pm (0.25\% \text{rdg} + 2 \text{ digits})$	0.1 mΩ
10 mA	10.00 Ω to 3000 Ω	±(0.25%rdg+1digit)	4 digits
	0.010 Ω to 9.999 Ω	$\pm (0.25\% \text{rdg} + 2 \text{ digits})$	0.001 Ω
1 mA	100.0Ωto30.00kΩ	±(0.25%rdg+1digit)	4 digits
	0.10 Ω to 99.99 Ω	$\pm (0.25\% \text{rdg} + 2 \text{ digits})$	0.01 Ω

### **INCLUDED ACCESSORIES**









### **OPTIONAL ACCESSORIES**



Transport case suited for the instrument and cables.

ORDERING INFORMAT	10	NI I			
Item	10	)IN	Order No.		
MTO106	BN-19090				
Included accessories	DIN-19090				
Test lead black with banana connector and Kelvin clamp, 10 m (33 ft)	1	GC-32310			
Test lead red with banana connector and Kelvin clamp, 10 m (33 ft)		GC-32312			
Ground lead, 5 m (16 ft) 2.5 mm <sup>2</sup>		GA-00200			
Mains cable		AA-00010			
User's manual		ZP-BN01E			
MTO106 Report pad		XP-BN01E			
MTO106 Reporting template file		SB-0022E			
Carry bag		2000-091			
MTO106 Without accessories	BN-19000				
Optional accessories					
Transport case for instrument and lea	1009-744				
MTO106 dual channel measurement Parts included in the MTO106 dual cl measurement lead set (GA-03310).	GA-03310				
Sensing lead, black, 10 m (33 ft)	1	KG-00530			
Sensing lead, red, 10 m (33 ft)		KG-00532			
Timing clamp		KD-03040			
Test cable, black, 2 m (6.5 ft)	1	04-35030			

Group exporter:
Multi-Tek International
Email: mti@multitekintl.com

